# xcite LED Lighting

# **Data Sheet**

Order Code: XCBHCWPX1

Prismatic diffuser - 3000K-6000K + Wattage Selectable - White



### **Features**

- Suitable for exterior commercial and industrial applications
- Wattage [8W,10W,12W] adjustable via 3-way selector switch
- CCT [3000K/4000K/6000K] adjustable via 3-way selector switch

#### Construction

- Modular emergency and microwave sensor's available for quick and easy conversion of a standard fitting
- For additional control, please use X1 Bulkhead Remote [Sold Separately]

### Installation Notes

3-point screw fixing Conduit side entry points for surface mount cable entry Loop-in, loop-out push-fit terminal block for quick tool-free instalation

















Driver Current (mA)

Forward Voltage (V)

## **Technical Data**

rediffical Bata				
General		Electrical		
Luminaire Wattage (W)	8W/12W/16W	Rated Input Current (A)	0.04 to 0.08	
Weight (kg)	0.69	Power Factor (pf)	0.82 to 0.92	
Operating Temperature (ta °C)	0° to 25°	Input Voltage Range (VAC)	198 to 264	
Light Output		Inrush Current Peak (A)	2.08	
	1200-2120	Surge Protection (kV)	1	
Efficacy (Im/W)	155	Conductor Size (mm)	0.5 to 2.5	
		Terminal Type	4 pole piano key	
LED				
CRI	80			
Macadam Elipses	0.9 to 1.4			

140/215/280

48.5 to 52.5

Driver

# xcite LED Lighting

# **Data Sheet**



Order Code: XCBHCWPX1

Prismatic diffuser - 3000K-6000K + Wattage Selectable - White

#### **Dimensions**

C (mm)	 85
Dia. (mm)	282

## Line Drawing



