

**Order Code: XCBHSWOX1MS**

X1 Bulkhead WP - Square - Opal diffuser - CCT [3000K/4000K/6000K] + Wattage Selectable - White - Microwave sensor



**Features**

- Suitable for exterior commercial and industrial applications
- CCT adjustable via selector switch [3000K/4000K/6000K]
- Wattage adjustable via selector switch [8W/12W/16W]

**Construction**

- Modular [emergency](#) and [microwave sensor](#)'s available for quick and easy conversion of a standard fitting
- For additional control, please use [X1 Bulkhead Remote](#) [Sold Separately]

**Installation Notes**

4-point screw fixing  
Conduit side entry points for surface mount cable entry  
Loop-in, loop-out push-fit terminal block for quick tool-free instalation



**Technical Data**

General		Electrical	
Luminaire Wattage (W)	8W/12W/16W	Rated Input Current (A)	0.04 to 0.07
Weight (kg)	0.72	Power Factor (pf)	0.83 to 0.92
Operating Temperature (ta °C)	0° to 25°	Input Voltage Range (VAC)	198 to 264
		Inrush Current Peak (A)	18.4
Light Output		Surge Protection (kV)	1
Lumens (lm)	1100 to 2000	Conductor Size (mm)	0.5 to 2.5
Efficacy (lm/W)	141	Terminal Type	4 pole piano key
LED			
CCT (K)	3000K/4000K/6000K		
CRI	80		
Macadam Elipses	1.0 to 1.6		
Driver			
Driver Current (mA)	140/215/280		
Forward Voltage (V)	48.5 to 52.5		

**Order Code: XCBHSWOX1MS**

X1 Bulkhead WP - Square - Opal diffuser - CCT [3000K/4000K/6000K] + Wattage Selectable - White - Microwave sensor

Dimensions

A (mm)	252
B (mm)	252
C (mm)	92

Line Drawing

