

**Order Code: XCBLM3**

3W - Emergency Exit Sign with Arrow Up Legend - 3hrs Maintained Emergency

**Features**

- Ideal for retrofit of existing emergency fixtures
- Suitable for ceiling, wall or surface fixings
- 20mm conduit rear cable entries
- Multi purpose LED emergency drop light
- Supplied with flag pole mounting kit

**Construction**

- Operates in maintained and non-maintained mode
- Supplied with EURO 4 running man legend

**Technical Data****General**

Luminaire Wattage (W)	3
Weight (kg)	0.79
Operating Temperature (ta °C)	5 to 25

**Electrical**

Rated Input Current (A)	0.039
Power Factor (pf)	0.3
Input Voltage Range (VAC)	220-240
Conductor Size (mm)	1.5
Terminal Type	4 pole screw down

**LED**

CCT (K)	6500
CRI	50

### Order Code: XCBLM3

3W - Emergency Exit Sign with Arrow Up Legend - 3hrs Maintained Emergency

#### Dimensions

A (mm)	344
B (mm)	237
C (mm)	42

#### Line Drawing

