

**Order Code:** XCBLM3  
3W - Emergency Exit Sign with Arrow Up Legend - 3hrs Maintained Emergency



Features

- Ideal for retrofit of existing emergency fixtures
- Suitable for ceiling, wall or surface fixings
- 20mm conduit rear cable entries
- Multi purpose LED emergency drop light
- Supplied with flag pole mounting kit

Construction

- Operates in maintained and non-maintained mode
- Supplied with EURO 4 running man legend



Technical Data

General		Electrical		
Luminaire Wattage (W)	3	Rated Input Current (A)	0.039	
Weight (kg)	0.79	Power Factor (pf)	0.3	
Operating Temperature (ta °C)	5 to 25	Input Voltage Range (VAC)	220-240	
LED		Conductor Size (mm)	1.5	
	CCT (K)	6500	Terminal Type	4 pole screw down
	CRI	50		

**Order Code:** XCBLM3  
3W - Emergency Exit Sign with Arrow Up Legend - 3hrs Maintained Emergency

Dimensions

A (mm)	344
B (mm)	237
C (mm)	42

Line Drawing

