xcite LED Lighting

Data Sheet



Order Code: XCBLM3ST

3W - Emergency Exit Sign with Arrow Up Legend - Self-test - 6500K



Features

- Ideal for retrofit of existing emergency fixtures
- Suitable for ceiling, wall or surface fixings
- 20mm conduit rear cable entries
- Multi purpose LED emergency drop light
- · Supplied with flag pole mounting kit

Construction

- Operates in maintained and non-maintained mode
- · Supplied with EURO 4 running man legend
- Integral auto self-test for reduced maintenance













Technical Data

General		Electrical	
Luminaire Wattage (W)	3	Rated Input Current (A)	0.039
Weight (kg)	0.79	Power Factor (pf)	0.3
Operating Temperature (ta °C)	5 to 25	Input Voltage Range (VAC)	220-240
LED		Conductor Size (mm)	1.5
CCT (K)	6500	Terminal Type	4 pole screw down
CRI	70		
Driver			
Forward Voltage (V)	3.3		



xcite LED Lighting

Data Sheet



Order Code: XCBLM3ST

3W - Emergency Exit Sign with Arrow Up Legend - Self-test - 6500K

Dimensions

A (mm)	344
B (mm)	237
C (mm)	42

Line Drawing

