

Order Code: XCBLM3ST
3W - Emergency Exit Sign with Arrow Up Legend - Self-test - 6500K



Features

- Ideal for retrofit of existing emergency fixtures
• Suitable for ceiling, wall or surface fixings
• 20mm conduit rear cable entries
• Supplied with flag pole mounting kit
• Multi purpose LED emergency drop light

Construction

- Operates in maintained and non-maintained mode
• Supplied with EURO 4 running man legend
• Integral auto self-test for reduced maintenance

6500K 3YRS WARRANTY IP20 IK06 M3

Technical Data

Table with 2 main sections: General and Electrical. General includes Luminaire Wattage (3W), Weight (0.79kg), Operating Temperature (5 to 25°C), LED CCT (6500K), CRI (70), and Driver Forward Voltage (3.3V). Electrical includes Rated Input Current (0.039A), Power Factor (0.3), Input Voltage Range (220-240V), Conductor Size (1.5mm), and Terminal Type (4 pole screw down).

Order Code: XCBLM3ST
3W - Emergency Exit Sign with Arrow Up Legend - Self-test - 6500K

Dimensions

A (mm)	344
B (mm)	237
C (mm)	42

Line Drawing

