

**Order Code: XCEBM3EU3**

4W - Emergency Exit Box with Arrow Down Legend - 3hrs Maintained Emergency



**Features**

- Ideal for replacement of linear fluorescent fixtures
- Suitable for escape routes and exits
- 20mm conduit side and rear cable entries BESA for wall fix
- Reduced maintenance and high performance

**Construction**

- Steel body
- Maintained or non-maintained available
- Supplied with EURO 4 running man legend



**Technical Data**

General		Electrical	
Luminaire Wattage (W)	4	Power Factor (pf)	0.4
Weight (kg)	1.41	Input Voltage Range (VAC)	220-240
Operating Temperature (ta °C)	5 to 25	Surge Protection (kV)	1
		Conductor Size (mm)	1.5
		Terminal Type	Piano Key
LED			
CCT (K)	6500		
CRI	60		
Driver			
Driver Current (mA)	340		
Forward Voltage (V)	2.8		

**Order Code:** XCEBM3EU3

4W - Emergency Exit Box with Arrow Down Legend - 3hrs Maintained Emergency

### Dimensions

A (mm)	392
B (mm)	190
C (mm)	60

### Line Drawing

