

Order Code: XCEBNM3

1W - Emergency Exit Box with Arrow Up Legend - 3hrs Non-Maintained Emergency



Features

- Ideal for replacement of linear fluorescent fixtures
- Suitable for escape routes and exits
- 20mm conduit side and rear cable entries BESA for wall fix
- Reduced maintenance and high performance

Construction

- Steel body
- Maintained or non-maintained available
- Supplied with EURO 4 running man legend



Technical Data

| General | | Electrical | |
|-------------------------------|---------|---------------------------|-----------|
| Luminaire Wattage (W) | 1 | Power Factor (pf) | 0.19 |
| Weight (kg) | 1.39 | Input Voltage Range (VAC) | 220-240 |
| Operating Temperature (ta °C) | 5 to 25 | Surge Protection (kV) | 1 |
| | | Conductor Size (mm) | 1.5 |
| | | Terminal Type | Piano Key |
| LED | | | |
| CCT (K) | 6500 | | |
| CRI | 60 | | |
| Driver | | | |
| Driver Current (mA) | 340 | | |
| Forward Voltage (V) | 2.8 | | |

Order Code: XCEBNM3

1W - Emergency Exit Box with Arrow Up Legend - 3hrs Non-Maintained Emergency

Dimensions

| | |
|--------|-----|
| A (mm) | 392 |
| B (mm) | 190 |
| C (mm) | 60 |

Line Drawing

