

**Order Code: XCEBNM3**

1W - Emergency Exit Box with Arrow Up Legend - 3hrs Non-Maintained Emergency



**Features**

- Ideal for replacement of linear fluorescent fixtures
- Suitable for escape routes and exits
- 20mm conduit side and rear cable entries BESA for wall fix
- Reduced maintenance and high performance

**Construction**

- Steel body
- Maintained or non-maintained available
- Supplied with EURO 4 running man legend



**Technical Data**

General		Electrical	
Luminaire Wattage (W)	1	Power Factor (pf)	0.19
Weight (kg)	1.39	Input Voltage Range (VAC)	220-240
Operating Temperature (ta °C)	5 to 25	Surge Protection (kV)	1
		Conductor Size (mm)	1.5
		Terminal Type	Piano Key
LED			
CCT (K)	6500		
CRI	60		
Driver			
Driver Current (mA)	340		
Forward Voltage (V)	2.8		

### Order Code: XCEBNM3

1W - Emergency Exit Box with Arrow Up Legend - 3hrs Non-Maintained Emergency

#### Dimensions

A (mm)	392
B (mm)	190
C (mm)	60

#### Line Drawing

