

**Order Code: XCEBNM3**

1W - Emergency Exit Box with Arrow Up Legend - 3hrs Non-Maintained Emergency



**Features**

- Ideal for replacement of linear fluorescent fixtures
- Suitable for escape routes and exits
- 20mm conduit side and rear cable entries BESA for wall fix
- Reduced maintenance and high performance

**Construction**

- Steel body
- Maintained or non-maintained available
- Supplied with EURO 4 running man legend



**Technical Data**

| General                       |         | Electrical                |           |
|-------------------------------|---------|---------------------------|-----------|
| Luminaire Wattage (W)         | 1       | Power Factor (pf)         | 0.19      |
| Weight (kg)                   | 1.39    | Input Voltage Range (VAC) | 220-240   |
| Operating Temperature (ta °C) | 5 to 25 | Surge Protection (kV)     | 1         |
|                               |         | Conductor Size (mm)       | 1.5       |
|                               |         | Terminal Type             | Piano Key |
| LED                           |         |                           |           |
| CCT (K)                       | 6500    |                           |           |
| CRI                           | 60      |                           |           |
| Driver                        |         |                           |           |
| Driver Current (mA)           | 340     |                           |           |
| Forward Voltage (V)           | 2.8     |                           |           |

**Order Code: XCEBNM3**

1W - Emergency Exit Box with Arrow Up Legend - 3hrs Non-Maintained Emergency

Dimensions

|        |     |
|--------|-----|
| A (mm) | 392 |
| B (mm) | 190 |
| C (mm) | 60  |

Line Drawing

