

Order Code: XCSBT631CTM3
31W - 1800mm Batten CC [3000K/4000K/6000K] - 3hrs Maintained Emergency



Features

- Ideal for replacement of linear fluorescent fixtures
- Suitable for general domestic and commercial use
- CCT [3000K/4000K/6000K] adjustable via 3-way selector switch
- Up to 135 lumens per watt efficacy

Construction

- Steel body in white finish
- High quality opal diffuser to reduce glare
- Integral high quality driver and LED module
- Loop in/out mains connector
- Conduit and BESA fixing points for end or rear cable entry



Technical Data

General		Electrical	
Luminaire Wattage (W)	31	Rated Input Current (A)	0.14
Weight (kg)	2.10	Power Factor (pf)	0.9
Operating Temperature (ta °C)	5 to 25	Input Voltage Range (VAC)	220-240
Light Output		Inrush Current Peak (A)	10
Lumens (lm)	4200	Surge Protection (kV)	1
Efficacy (lm/W)	135	Conductor Size (mm)	1.5
LED		Terminal Type	4 pole piano key
CCT (K)	TRI-COLOUR		
CRI	80		
Macadam Ellipses	4		
Driver			
Driver Current (mA)	750		
Forward Voltage (V)	24-42		
Emergency			
Emergency Lumen Operating	190		
Emergency Wattage (W)	1		

Order Code: XCSBT631CTM3
31W - 1800mm Batten CC [3000K/4000K/6000K] - 3hrs Maintained Emergency

Dimensions

A (mm)	1800
B (mm)	55
C (mm)	58
Fix	610

Line Drawing

