

Order Code: XCSBT631DLM3P

31W - 1800mm Batten - 6000K - 3hrs Maintained Emergency - Batten fit PIR

Features

- Ideal for replacement of linear fluorescent fixtures
- Suitable for general domestic and commercial use
- Batten fit PIR option available
- Up to 131 lumens per watt efficacy

Construction

- Steel body in white finish
- High quality opal diffuser to reduce glare
- Integral high quality driver and LED module
- Loop in/out mains connector
- Conduit and BESA fixing points for end or rear cable entry
- Available in warm white [3000K], neutral white [4000K] or daylight [6000K]



Technical Data

General		Electrical	
Luminaire Wattage (W)	31	Rated Input Current (A)	0.14
Weight (kg)	1.80	Power Factor (pf)	0.9
Operating Temperature (ta °C)	5 to 25	Input Voltage Range (VAC)	220-240
Light Output		Inrush Current Peak (A)	10
		Surge Protection (kV)	1
		Conductor Size (mm)	1.5
Lumens (lm)	4050	Terminal Type	4 pole piano key
Efficacy (lm/W)	131		
LED			
CCT (K)	6000		
CRI	80		
Macadam Elipses	4		
Emergency			
Emergency Lumen Operating	190		
Emergency Wattage (W)	1		

Order Code: XCSBT631DLM3P

31W - 1800mm Batten - 6000K - 3hrs Maintained Emergency - Batten fit PIR

Dimensions

A (mm)	1921
B (mm)	55
C (mm)	58
Fix	610

Line Drawing

