

### Order Code: XCSBT631NWM3

31W - 1800mm Batten - 4000K - 3hrs Maintained Emergency

#### Features

- Ideal for replacement of linear fluorescent fixtures
- Suitable for general domestic and commercial use
- Batten fit PIR option available
- Up to 131 lumens per watt efficacy

#### Construction

- Steel body in white finish
- High quality opal diffuser to reduce glare
- Integral high quality driver and LED module
- Loop in/out mains connector
- Conduit and BESA fixing points for end or rear cable entry
- Available in warm white [3000K], neutral white [4000K] or daylight [6000K]



#### Technical Data

General		Electrical	
Luminaire Wattage (W)	31	Rated Input Current (A)	0.14
Weight (kg)	1.70	Power Factor (pf)	0.9
Operating Temperature (ta °C)	5 to 25	Input Voltage Range (VAC)	220-240
		Inrush Current Peak (A)	10
		Surge Protection (kV)	1
		Conductor Size (mm)	1.5
		Terminal Type	4 pole piano key
Light Output			
Lumens (lm)	4050		
Efficacy (lm/W)	131		
LED			
CCT (K)	4000		
CRI	80		
Macadam Elipses	4		
Emergency			
Emergency Lumen Operating	190		
Emergency Wattage (W)	1		

**Order Code:** XCSBT631NWM3

31W - 1800mm Batten - 4000K - 3hrs Maintained Emergency

### Dimensions

A (mm)	1800
B (mm)	55
C (mm)	58
Fix	610

### Line Drawing

