

### Order Code: XCSBT631WWM3

31W - 1800mm Batten - 3000K - 3hrs Maintained Emergency

#### Features

- Ideal for replacement of linear fluorescent fixtures
- Suitable for general domestic and commercial use
- Batten fit PIR option available
- Up to 124 lumens per watt efficacy

#### Construction

- Steel body in white finish
- High quality opal diffuser to reduce glare
- Integral high quality driver and LED module
- Loop in/out mains connector
- Conduit and BESA fixing points for end or rear cable entry
- Available in warm white [3000K], neutral white [4000K] or daylight [6000K]



#### Technical Data

##### General

|                               |         |
|-------------------------------|---------|
| Luminaire Wattage (W)         | 31      |
| Weight (kg)                   | 1.70    |
| Operating Temperature (ta °C) | 5 to 25 |

##### Light Output

|                 |      |
|-----------------|------|
| Lumens (lm)     | 3850 |
| Efficacy (lm/W) | 124  |

##### LED

|                 |      |
|-----------------|------|
| CCT (K)         | 3000 |
| CRI             | 80   |
| Macadam Elipses | 4    |

##### Emergency

|                           |     |
|---------------------------|-----|
| Emergency Lumen Operating | 190 |
| Emergency Wattage (W)     | 1   |

##### Electrical

|                           |                  |
|---------------------------|------------------|
| Rated Input Current (A)   | 0.14             |
| Power Factor (pf)         | 0.9              |
| Input Voltage Range (VAC) | 220-240          |
| Inrush Current Peak (A)   | 10               |
| Surge Protection (kV)     | 1                |
| Conductor Size (mm)       | 1.5              |
| Terminal Type             | 4 pole piano key |

**Order Code:** XCSBT631WWM3

31W - 1800mm Batten - 3000K - 3hrs Maintained Emergency

### Dimensions

|        |      |
|--------|------|
| A (mm) | 1800 |
| B (mm) | 55   |
| C (mm) | 58   |
| Fix    | 610  |

### Line Drawing

