

Order Code: XCSEBM3ST

4W - Emergency Exit Box [Arrow Up] - Fixed Output - Emergency Self-test - 6500K



Features

- Suitable for escape routes and exits
- Rear BESA fix and 3 additional rear fixing points
- Dual LED array for internal illumination and downward distribution
- Reduced maintenance and high performance
- Only 30mm depth for modern, slimline appearance

Construction

- Plastic body
- Hinged front lid for easy installation
- Supplied with universal EURO running man legend
- Integral auto self-test with disable function



Technical Data

General		Electrical		
Luminaire Wattage (W)	3	Rated Input Current (A)	0.029	
Weight (kg)	0.65	Power Factor (pf)	0.46	
Operating Temperature (ta °C)	5 to 25	Input Voltage Range (VAC)	220-240	
LED		Conductor Size (mm)	1.5	
	CCT (K)	6500	Terminal Type	4 pole screw down
	CRI	70		
Driver				
Driver Current (mA)	172			
Forward Voltage (V)	2.7			

**Order Code:** XCSEBM3ST  
4W - Emergency Exit Box [Arrow Up] - Fixed Output - Emergency Self-test - 6500K

Dimensions

A (mm)	325
B (mm)	185
C (mm)	30

Line Drawing

