# xcite LED Lighting

### **Data Sheet**



Order Code: XCSEBM3ST

4W - Emergency Exit Box [Arrow Up] - Fixed Output - Emergency Self-test - 6500K



### **Features**

- · Suitable for escape routes and exits
- Rear BESA fix and 3 additional rear fixing points
- Dual LED array for internal illumination and downward distribution
- Reduced maintenance and high performance
- Only 30mm depth for modern, slimline appearance

#### Construction

- Plastic body
- Hinged front lid for easy installation
- Supplied with universal EURO running man legend
- Integral auto self-test with disable function













**Technical Data** 

General		
Luminaire Wattage (W)	3	
Weight (kg)	0.65	
Operating Temperature (ta °C)		
LED		
CCT (K)	6500	
CRI	70	
Driver		
Driver Current (mA)	172	
Forward Voltage (V)	2.7	

Electrical	
Rated Input Current (A)	0.029
Power Factor (pf)	0.46
Input Voltage Range (VAC)	220-240
Conductor Size (mm)	1.5
Terminal Type	4 pole screw down



# xcite LED Lighting

## **Data Sheet**



### Order Code: XCSEBM3ST

4W - Emergency Exit Box [Arrow Up] - Fixed Output - Emergency Self-test - 6500K

### **Dimensions**

A (mm)	325
B (mm)	185
C (mm)	30

### Line Drawing



