

Order Code: XCSEDL1NM3CST

1W - Fixed Output - Non-maintained Emergency Self-test - Corridor Function - 6500K

**Features**

- Suitable for open areas and escape routes
- 20mm conduit side and rear cable entries
- Virtually service free emergency lighting
- Easy to install with simple connection wiring

Construction

- Very low energy consumption - 1W
- Polycarbonate body
- Operates in non-maintained mode
- Internal mains connection
- Integral auto self-test for reduced maintenance, includes a disable function

Technical Data**General**

Luminaire Wattage (W)	1
Weight (kg)	0.37
Operating Temperature (ta °C)	5 to 25

LED

CCT (K)	6500
CRI	70

Driver

Driver Current (mA)	350
Forward Voltage (V)	3.1

Emergency

Emergency Lumen Operating	140
Emergency Wattage (W)	1

Electrical

Rated Input Current (A)	0.035
Input Voltage Range (VAC)	220-240
Conductor Size (mm)	1.5
Terminal Type	3 pole screw down

Order Code: XCSEDL1NM3CST

1W - Fixed Output - Non-maintained Emergency Self-test - Corridor Function - 6500K

Dimensions

A (mm)	170
B (mm)	120
C (mm)	45

Line Drawing

