xcite LED Lighting
Data Sheet

Order Code: XCBLM3EU3

3W - Emergency Exit Sign with Arrow Down Legend - 3hrs Maintained Emergency



Features

- Ideal for retrofit of existing emergency fixtures
- Suitable for ceiling, wall or surface fixings
- 20mm conduit rear cable entries
- Multi purpose LED emergency drop light
- Supplied with flag pole mounting kit

Construction

- Operates in maintained and non-maintained mode
- Supplied with EURO 4 running man legend

50,000 HOURS | 3YRS WARRANTY | IP20 | IK06 | M3

Technical Data

General

Luminaire Wattage (W)	3
Weight (kg)	0.79
Operating Temperature (ta °C)	5 to 25

LED

CCT (K)	6500
CRI	50

Electrical

Rated Input Current (A)	0.039
Power Factor (pf)	0.3
Input Voltage Range (VAC)	220-240
Conductor Size (mm)	1.5
Terminal Type	4 pole screw down

Technical
Stafford Park 12
Telford, Shropshire,
TF3 3BJ

T: +44 (0)1952 292441
E: sales@xciteledlighting.co.uk
W: www.xciteledlighting.co.uk

Order Code: XCBLM3EU3

3W - Emergency Exit Sign with Arrow Down Legend - 3hrs Maintained Emergency

Dimensions

Length (mm)	344
Width (mm)	237
Depth (mm)	42

Technical
Stafford Park 12
Telford, Shropshire,
TF3 3BJ

T: +44 (0)1952 292441
E: sales@xciteledlighting.co.uk
W: www.xciteledlighting.co.uk