

Order Code: XCEBAM3ST

XCITE EXIT BOX ST XCEBA 3W - 6500K - Fixed output - Emergency Self-test



Features

- Ideal for replacement of linear fluorescent fixtures
- Suitable for escape routes and exits
- 20mm conduit top and rear cable entries BESA for wall fix
- Reduced maintenance and high performance
- EURO 1, 2 and 3 running man legend also available [sold separately]

Construction

- Steel body
- Maintained or non-maintained available
- Supplied with EURO 4 running man legend
- Integral auto self-test for reduced maintenance, includes a disable function
- Supplied with LiFePO4 battery



Technical Data

General		Electrical	
Luminaire Wattage (W)	3	Rated Input Current (A)	0.05
Weight (kg)	1.24	Power Factor (pf)	0.25
Operating Temperature (ta °C)	5° to 25°	Input Voltage Range (VAC)	220 to 240
		Conductor Size (mm)	1.5
		Terminal Type	4 pole push down
Driver			
Driver Current (mA)	340		
Forward Voltage (V)	2.57		

Order Code: XCEBAM3ST

XCITE EXIT BOX ST XCEBA 3W - 6500K - Fixed output - Emergency Self-test

Dimensions

A (mm)	392
B (mm)	190
C (mm)	60

Line Drawing

