

**Order Code: XCUCL8CT**

CABINET LIGHT CC Cabinet/Shaver Lights 8W - 3000K-4000K



**Features**

- CCT adjustable via 2-way selector switch [3000K/4000K]
- Slimline profile for discreet installation
- Up to 100 lumens per watt efficacy

**Construction**

- Extruded plastic body
- LED SMD modules array



**Technical Data**

General		Electrical	
Luminaire Wattage (W)	8	Rated Input Current (A)	0.04
Weight (kg)	0.14	Power Factor (pf)	0.9
Operating Temperature (ta °C)	0 to 25	Input Voltage Range (VAC)	220-240
<b>Light Output</b>		Inrush Current Peak (A)	5
Lumens (lm)	800	Surge Protection (kV)	0.5
Efficacy (lm/W)	100	Conductor Size (mm)	0.5 to 2.5
<b>LED</b>		Terminal Type	2 core flex
CCT (K)	3000K/4000K		
CRI	80		
Macadam Ellipses	5		
<b>Driver</b>			
Driver Current (mA)	180		
Forward Voltage (V)	36		

**Order Code:** XCUCL8CT

CABINET LIGHT CC Cabinet/Shaver Lights 8W - 3000K-4000K

### Dimensions

A (mm)	529
B (mm)	23
C (mm)	37

### Line Drawing

